

Retail Store: small





High quality audio for BGM and paging


System Overview

A simple but high quality audio system has been provided to enhance the customers' shopping experience. Simply connecting the source music player and microphone to an MA2030 mixing amplifier, and the outputs of the MA2030 to the store's speaker system, results in a well-balanced high performance BGM system that contributes greatly to the overall atmosphere. The MA2030 interface is easy to use and can be directly operated without difficulty, and a remote DCP control panel located at the sales counter adds even further convenience.

Key Features

- Yamaha CIS speaker systems are specially tuned for music applications and are the best solution for BGM delivery, even when only low volume levels are required.
- The MA2030 is a compact amplifier designed for small applications that offers a range of powerful features such as a Priority Ducker that automatically turns the music down while announcements are being made.
- Daily operations such as volume adjustment can be easily carried out from the intuitive remote DCP control panel.







Component List


Name	VX55 speaker	DCP1V4S controller	MA2030 mixer amplifier	CD-C600RK CD player	
Qty	4	1	1	1	


Cable List

Name	analog cable	speaker cable: 100V	CAT5E cable
Length	10m	45m	10m

VXS5 speaker 	Speaker type 2-way, Bass reflex Components LF 5.25" Cone HF 0.75" Soft dome Coverage Angle (H x V) 120° x 120° Nominal Impedance 8Ω
	Power Rating PGM 150W Sensitivity (1W,1m) 89dB SPL Frequency Range (-10dB) 62Hz - 20kHz Connectors 1x Euroblock (4P) (Input: + / -, Loop Thru: + / -) Transformer Taps 70V 30W (170Ω), 15W (330Ω), 7.5W (670Ω), 3.8W (1.3kΩ) 100V 30W (330Ω), 15W (670Ω), 7.5W (1.3kΩ) Environmental IP35 Dimensions (W x H x D) 176 x 280 x 163mm (6.9 x 11.0 x 6.4") Weight 3.6kg (7.9lbs)

DCP1V4S controller 	Connectors 2x RJ45 Wiring Max cable length up to 200m, Up to 8 controllers per 1MTX with CAT5 cable Control RS485, Power over Ethernet Dimensions (WxHxD) US: 70 x 120 x 47mm (2.8 x 5.5 x 1.9") EU: 86 x 86 x 47mm (3.4 x 3.4 x 1.9") not including wall box Weight US: 118g (0.26lbs) EU: 110g (0.24lbs)
---	--

MA2030 mixer amplifier 	Output Power 1kHz, THD+N = 1% 3Ω/4Ω 30W x 2 High impedance 70V/100V 60W x 1 Input Level (Stereo Input) Unbalanced Sensitivity -10.0 dBV Nominal -10.0 dBV Max before clip +10.0 dBV Nominal -10.0 dBV Output Level (Line Out) Stereo in (Line in) to Speaker out; 1kHz, 15W, 3Ω/4Ω ≤ 0.1% Stereo in (Line in) to Speaker out; 1kHz, 30W, 70V/100V ≤ 0.2% THD+N Stereo in (Line in) to Speaker out; 50Hz to 20kHz, 1W, 3Ω/4Ω 0dB, -2.5dB, +1.0dB Stereo in (Line in) to Speaker out; 50Hz to 20kHz, 1W, 70V/100V 0dB, -3.0dB, +1.0dB Frequency Response Stereo in (Line in) to Speaker out; 90Hz to 20kHz, 1W, 70V/100V 0dB, -3.0dB, +1.0dB Power Requirement 100V, 120V, 230V-240V; 50Hz/60Hz Dimensions (WxHxD) 215 x 54 x 288 mm (8.5" x 2.1" x 11.4") Weight 1.8kg (4.0lbs)
--	---

CD-C600RK CD player 	Frequency Response(±0.5dB) 20Hz-20kHz Harmonic Distortion+Noise ≤0.003% Signal-to-Noise Ratio ≥105dB Dynamic range ≥96 dB Output Level (1kHz, 0dB) 2±0.3V Dimensions (W x H x D) 480 x116 x 405mm (18.9" x 4-5/8" x 16") Weight 6.9kg (15.2lbs)
---	--